

* To configure this printer for your Sircle POS, you will need Windows computer *

- 1. Download ByNetWinConfig Tool
 - <u>https://sirclepos.squarespace.com/s/BYNetWinConfigV3_10.z</u>
 <u>ip</u>
- 2. Extract the contents of the zip file



Page 2 of BTP-R180II installation

3. Once extracted, go into the folder and run the BYNetWinconfig.exe



Page 3 of BTP-R180II installation

4. Open I	Protocol Operation	n(O)
Net WinConfig 1	ōol V3.10	
Name	IP	MAC 简体中文 English
		Protocol Operation(<u>O</u>)
		Search Printers(<u>S</u>)
		Wireless Parameter Setting(<u>M</u>
		IP Parameter Setting(<u>l</u>)
		Interface Firmware Update(U
		Printer Status(<u>C</u>)
		Print Test Page(<u>P</u>)
		Reboot Device(<u>R</u>)
		Exit(E)

Page 4 of BTP-R180II installation

5. Make sure IPv4 and UDP (Inter-segment) are selected then click OK

BYNet WinCo	Select protocol	\mathbf{x}
Name	1. Please select IP protocol type: IPv4 IPv6 2. Please select protocol to search and configure printers: OUDP	English on(<u>Q</u>)
	Support JK-E01, JK-E02, JK-W01 and JK-W03 OUDP (Inter-segment)	s(<u>S)</u>
	Support JK-E02(FV2.010 or above), JK-E04, JK-E05 and JK-W03	Setting(<u>W</u>) tting(<u>I</u>)
	OUDP and IPX/SPX Support JK-E01, JK-E02, JK-W01 and JK-W03	Jpdate(<u>U</u>)
	OMulticast Support JK-W03	(<u>C</u>)
	3. Please specify ip address range: No Yes Support JK-E01, JK-E02, JK-W01 and JK-W03 Start:	e(<u>P)</u> (<u>R)</u>
After searche	End: OK(<u>O</u>) Return(<u>R</u>)	

Page 5 of BTP-R180II installation

6. Now click Search Printers. The printer will show up to the left. Click OK.

BYN	et WinConfig Tool	V3.10		×
	Name	IP	MAC	简体中文 English
1	BTP-R180II	10.0.0.61	00134	Protocol Operation(<u>O</u>)
			BYNetWinConfig	Wireless Parameter Setting(<u>W</u>)
			Search printer completely!	IP Parameter Setting(<u>I</u>)
				Interface Firmware Update(U)
_				Printer Status(<u>C</u>)
				Print Test Page(<u>P</u>)
				Reboot Device(<u>R</u>)
•			4	Exit(<u>E</u>)
After	searched device	s,please select	the device before other operation	l.

THE PRINTER WILL INITIALLY HAVE AN IP ADDRESS WHICH DOES NOT MATCHES YOUR NETWORK NEXT FEW STEPS WE WILL FIX THIS

7. Select the printer and then click IP Parameter Setting

BYNet WinConfig Tool	V3.10		×
Name	IP	MAC	简体中文 English
1 BTP-R180I	10.0.0.61	00134	Protocol Operation(<u>O</u>)
			Search Printers(<u>S</u>)
			Wireless Parameter Setting(<u>W</u>)
			IP Parameter Setting(I)
			Interface Firmware Update(U)
			Printer Status(<u>C</u>)
			Print Test Page(<u>P</u>)
			Reboot Device(<u>R</u>)
< <u> </u>		+	Exit(E)
After searched device	es,please select the device be	fore other operation.	

Page 7 of BTP-R180II installation

8. Make sure that Dynamic IP Address(DHCP) is selected then click ok

	Network parameter setting	9				V C	eed_test			
BYNet WinConfig	Oynamic IP Addres	ss(DHC	P)							
Name	DHCP Tim	eout:	90		s		Fnglish			
1 BTP-R180	-CFixed IP Address									
	IP Address:	10	0	0	61		eration(<u>O</u>)			
	Subnet Mask:	255	255	255	0		nters(<u>S)</u>			
	Gateway Address:	10	0	0	1		ter Setting(<u>W</u>)			
	PING IPv6 Assignment Method :									
	IPv6 address :					/	ire Update(<u>U)</u>			
	Create Password New Pass	word:					atus(<u>C)</u>			
	New Password A	gain:					Page(<u>P)</u>			
	Configure Print por New Print	t Port:	9100				wice(<u>R</u>)			
<	□ Restore Default Co □ JK-E05 turn on an	onfigura alarm v	tion when the	e net wi	e is out		Ξ)			
After searched d	<u> </u>		R	eturn(<u>R</u>			5128: 920 KD			
	1						_1			

Page 8 of BTP-R180II installation

9. Now click Reboot Device

	Name	IP	MAC	简体中文 English
1	BTP-R180II	10.0.0.61	00134	
				Protocol Operation(<u>O</u>)
				Search Printers(S)
				Wireless Parameter Setting(<u>W</u>)
				IP Parameter Setting(I)
				Interface Firmware Update(U)
				Printer Status(<u>C</u>)
				Print Test Page(P)
				Reboot Device(<u>R</u>)
•			4	Exit(<u>E</u>)

Page 9 of BTP-R180II installation

10. After printer feeds paper, click Search Printers again.

BYN	let WinConfig Tool V	3.10		\times
	Name	IP	MAC	简体由文 English
1	BTP-R180II	10.0.0.61	00134	
				Protocol Operation(<u>O</u>)
				Search Printers(<u>S</u>)
				Wireless Parameter Setting(<u>W</u>)
				IP Parameter Setting(<u>I</u>)
				Interface Firmware Update(U)
				Printer Status(<u>C</u>)
				Print Test Page(<u>P</u>)
				Reboot Device(<u>R</u>)
•	III		4	Exit(E)
Afte	r searched devices	please select the device before	other operation.	

TAKE NOTE OF THE IP ADDRESS TO INPUT INTO SIRCLE POS IT SHOULD NOW MATCH YOUR NETWORK

Page 10 of BTP-R180II installation

11. Click settings button on upper right (assuming you are now logged on)



Page 11 of BTP-R180II installation

12. Now click Printer Setup

Application Setup Printer Setup Payment Device Setup ADMINISTRATOR Payment Processing Database Settings Print Last Z-Out Report Print X-Out Report	JENERAL
Printer Setup ADMINISTRATOR Payment Processing Database Settings Print Last Z-Out Report C C C C C C C C C C C C C C C C C C C	Application Setup
Payment Device Setup ADMINISTRATOR Payment Processing Database Settings Print Last Z-Out Report Print X-Out Report	Printer Setup
ADMINISTRATOR Payment Processing Database Settings Print Last Z-Out Report Print X-Out Report	Payment Device Setup
Payment Processing Database Settings Print Last Z-Out Report Print X-Out Report	ADMINISTRATOR
Database Settings Print Last Z-Out Report Print X-Out Report	Payment Processing
Print Last Z-Out Report Print X-Out Report	Database Settings
Print X-Out Report	Print Last Z-Out Report
	Print X-Out Report
	ц,

Page 12 of BTP-R180II installation

13. Now click on Printer Type to flip the switch to on

Printer Type None			0
Choose Bluetooth Printer			
Click to Print Test Page Before testing, press the feed but	ion on the printer. After pressing this button the	printer will print a blank page and the c	ash register will open.
Printer Type			0
IP Address of Wifi Printer			
2			

14. Now click on IP Address of Wifi Printer

Printer Type None					0
Choose Bluetooth Printer					
Click to Print Test Page Before testing, press the feed buttor	i on the printer. After p	ressing this button	the printer will print	a blank page and the	cash register will open.
Printer Type Wifi					
IP Address of Wifi Printer					
2	Ц,	τ C		」 》	

15. Now input the IP Address you took note of earlier and then click OK

																	8	😵 🖥 5:34 рм
	Printe None	r Type		IP A	ddres	S									Т			
			h Print	Pleas	e type	the ip	adres	s of w	ifi print	er								
	Click t Before t	o Print Test testing, press t r Type	t Page he feed I	10.0.0	0.61	Canad						Ok						
						Lance	2					118						Ŷ
1		2	3		4		5		6		7		8		9		0	×
	@	#	:	\$		%		&		-		+		()		←
~	[<	<u>۱</u>	=		*		II		'		:		;		!		?	~[<
A	BC	,	-	,											/			٢
$\ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ $	2				Ĵ		\rangle		\Box				J»					

Page 15 of BTP-R180II installation

16. On the point of sale side, when you ring an item up, scroll to the right where it has the Open Drawer button and click Kitchen Order.

							U V 12.03 PM
search	*		0.00		С	Show Depar	Non-Tax De
# Qty Des	cription Price	% Tax X		2	3		
1 1 00003@8. Stockfish	59 Bits 8.59	% (Tax) 🗙	\rightarrow	-		Tax1 Dept	Tax2 Dept
			4	0	•	Tax3Dept	
			7	8	9		
			00	0	+/-		
			Non-Taxa e Item	abl	Kleenex	Tilapia - Smoked 9.99	Attieke - Choice 5.99
Quick Add Items	1 - Guest Customer	Kitchen Order	Story		Shakpa - S alone 3.59	Plantain B y Case 32.00	FooFoo-F atuku 2.50
Subtotal Tax GrandTotal	8.59 0.43 9.02	PAY	Cassava Fresh 1.29		Black Eyed Peas 0.99	Cocoa - Fr esh 1.29	Sweet Pota toe 2 1,39
\bigtriangleup	¢	t) (Ē	J »		R R R R R R R R R R R R R R R R R R R

Page 16 of BTP-R180II installation

17. After clicking Kitchen Order button, you will have the option to input a note, such as a customer requirement. Once you click OK it will print a note at your BTP-R180II.

9	0 😵 🗮 12:1	0 рм
search	Note Ppar Non-Tax De	
1 1 00003@8.59 Stockfish Bits	Please write the requirment.	
	extra <u>crispy</u>	
	Cancel	
	frisky crispy crossly	Ŷ
q w e	e ³ r ⁴ t ⁵ y ⁶ u ⁷ i ⁸ o ⁹ p ⁴	
a s	dfghjkl 🕂	
순 z	x c v b n m ! ? 🏠	
?123 ,	. 🦉 😌)
\bigtriangleup		

Customer Name: 1 - Guest Customer Stockfish Bits 1.0 extra crispy

Page 17 of BTP-R180II installation